

| | |
|-----------------------------------|--|
| 8-pin DIP Device Adapters | |
| DVA12XP080 | PIC12C5XX pinout |
| | 2.5V – 5.5V operation |
| DVA12XP081 | PIC12C67X pinout |
| | 2.5V – 5.5V operation |
| | Processor module connections differ from DVA12XP080 |
| 14-pin DIP Device Adapters | |
| DVA16XP140 | PIC16C505 pinout |
| | 2.5V – 5.5V operation |
| DVA16XP141 | PIC16F676 pinout |
| | 2.5V – 5.5V operation |
| 18-pin DIP Device Adapters | |
| DVA16XP180 | PIC16C5X pinout |
| | 2.5V – 5.5V operation |
| DVA16XP182 | PIC16C716 pinout |
| | 2.5V – 5.5V operation |
| | Timer1 oscillator on RB1/RB2 (Controlled by switches) |
| | Processor module connections differ from DVA16XP180 |
| DVA16XP187 | PIC16F716 pinout |
| | 2.5V – 5.5V operation |
| | Timer1 oscillator on RB1/RB2 (Controlled by switches) |
| | Processor module connections differ from DVA16XP182 |
| DVA16XP183 | PIC16F628 pinout |
| | 2.5V – 5.5V operation |
| | Timer1 oscillator on RB6/RB7 |
| DVA16XP186 | PIC16F648A pinout |
| | 2.5V – 5.5V operation |
| | Timer1 oscillator on RB6/RB7 |
| | Processor module connections differ from DVA16XP183 |
| DVA16XP184 | PIC16C717 pinout |
| | 2.5V – 5.5V operation |
| DVA18XP180 | Supersedes DVA16XP184 |
| | 2.5V – 5.5V operation |
| | Allows Timer1 oscillator to function properly on PIC18F devices |
| DVA16XP185 | PIC16C433 pinout |
| | 2.5V – 5.5V operation |
| DVA1001 | Supersedes DVA16XP187 |
| | PIC16F716 pinout |
| | Added support for 2.0V – 5.5V Operation |
| | Timer1 oscillator on RB1/RB2 (Software controlled by T1OSCEN bit in T1CON) |
| DVA1006 | Supersedes DVA16XP186 |
| | PIC16F648A pinout |
| | Added support for 2.0V – 5.5V Operation |
| | Timer1 oscillator on RB6/RB7 |
| 20-pin DIP Device Adapters | |
| DVA16XP200 | PIC16C770 pinout |
| | 2.5V – 5.5V operation |
| | Timer1 oscillator on RB6/RB7 |
| DVA16XP201 | PIC16C432 pinout |
| | 2.5V – 5.5V operation |
| DVA16XP202 | PIC16C782 pinout |
| | 2.5V – 5.5V operation |
| | Timer1 oscillator on OSC1/OSC2 |
| 28-pin DIP Device Adapters | |
| DVA14XP280 | PIC14000 pinout |
| | 2.5V – 5.5V operation |
| DVA16XP280 | PIC16C5X pinout |
| | 2.5V – 5.5V operation |
| DVA16XP281 | PIC16C6X/7X pinout |

| | |
|------------------------------------|---|
| | 2.5V – 5.5V operation |
| DVA16XP282 | Supersedes DVA16XP281 |
| | 2.5V – 5.5V operation |
| | Added support for RA6 digital I/O |
| | Added support for OSC2 (FOSC/4) clock out in EC oscillator mode |
| | Added support for Timer1 oscillator |
| DVA18XP280 | Supersedes DVA16XP282 |
| | 2.5V – 5.5V operation |
| | Added support for RA7 digital I/O |
| | Added support for OSC2 (FOSC/4) clock out frequency in Primary, RC and Secondary oscillator modes |
| 40-pin DIP Device Adapters | |
| DVA16XP400 | PIC16C6X/7X pinout |
| | 2.5V – 5.5V operation |
| DVA16XP401 | Supersedes DVA16XP400 |
| | 2.5V – 5.5V operation |
| | Added support for RA6 digital I/O |
| | Added support for OSC2 (FOSC/4) clock out in EC oscillator mode |
| | Added support for Timer1 Oscillator |
| DVA17XP400 | PIC17C4X pinout |
| | 2.5V – 5.5V operation |
| DVA17XP401 | Supersedes DVA17XP400 |
| | 2.5V – 5.5V operation |
| | Added support for OSC2 (FOSC/4) clock out in EC oscillator mode |
| DVA18XP400 | Supersedes DVA16XP401 |
| | 2.5V – 5.5V operation |
| | Added support for RA7 digital I/O |
| | Added support for OSC2 (FOSC/4) clock out frequency in Primary, RC and Secondary oscillator modes |
| 44-pin TQFP Device Adapters | |
| DVA16PQ440 | PIC16C6X/7X pinout |
| | 2.5V – 5.5V operation |
| DVA16PQ441 | Supersedes DVA16PQ440 |
| | 2.5V – 5.5V operation |
| | Added support for RA6 digital I/O |
| | Added support for OSC2 (FOSC/4) clock out in EC oscillator mode |
| | Added support for Timer1 Oscillator |
| DVA17PQ440 | PIC17C4X pinout |
| | 2.5V – 5.5V operation |
| DVA17PQ441 | Supersedes DVA17PQ440 |
| | 2.5V – 5.5V operation |
| | Added support for OSC2 (FOSC/4) clock out in EC oscillator mode |
| DVA18PQ440 | Supersedes DVA16PQ441 |
| | 2.5V – 5.5V operation |
| | Added support for RA7 digital I/O |
| | Added support for OSC2 (FOSC/4) clock out frequency in Primary, RC and Secondary oscillator modes |
| 44-pin PLCC Device Adapters | |
| DVA16XL440 | PIC16C6X/7X pinout |
| | 2.5V – 5.5V operation |
| DVA16XL441 | Supersedes DVA16XL440 |
| | 2.5V – 5.5V operation |
| | Added support for RA6 digital I/O |
| | Added support for OSC2 (FOSC/4) clock out in EC oscillator mode |
| | Added support for Timer1 oscillator |
| DVA17XL440 | PIC17C4X pinout |
| | 2.5V – 5.5V operation |
| DVA17XL441 | Supersedes DVA17XL440 |
| | 2.5V – 5.5V operation |
| | Added support for OSC2 (FOSC/4) clock out in EC oscillator mode |

| | |
|---|---|
| 64-pin DIP Device Adapter | |
| DVA16XP640 | PIC16C923/924 pinout |
| | 2.5V – 5.5V operation |
| 64-pin TQFP Device Adapter | |
| DVA16PQ640 | PIC16C92X pinout |
| | 2.5V – 5.5V operation |
| DVA17PQ640 | PIC17C75X pinout |
| | 2.5V – 5.5V operation |
| DVA17PQ641 | Supersedes DVA17PQ640 |
| | 2.5V – 5.5V operation |
| | Added support for OSC2 (FOSC/4) clock out in EC oscillator mode |
| DVA18PQ640 | PIC18C658 pinout |
| | 2.5V – 5.5V operation |
| 68-pin PLCC Device Adapter | |
| DVA16XL680 | PIC16C92X pinout |
| | 2.5V – 5.5V operation |
| DVA17XL680 | PIC17C75X pinout |
| | 2.5V – 5.5V operation |
| DVA17XL681 | Supersedes DVA17XL680 |
| | 2.5V – 5.5V operation |
| | Added support for OSC2 (FOSC/4) clock out in EC oscillator mode |
| DVA18XL680 | PIC18C658 pinout |
| | 2.5V – 5.5V operation |
| 80-pin TQFP Device Adapter | |
| DVA17PQ800 | PIC17C76X pinout |
| | 2.5V – 5.5V operation |
| DVA17PQ801 | Supersedes DVA17PQ800 |
| | 2.5V – 5.5V operation |
| | Added support for OSC2 (FOSC/4) clock out in EC oscillator mode |
| DVA18PQ800 | PIC18C858 pinout |
| | 2.5V – 5.5V operation |
| 84-pin PLCC Device Adapter | |
| DVA17XL840 | PIC17C76X pinout |
| | 2.5V – 5.5V operation |
| DVA17XL841 | Supersedes DVA17XL840 |
| | 2.5V – 5.5V operation |
| | Added support for OSC2 (FOSC/4) clock out in EC oscillator mode |
| DVA18XL840 | PIC18C858 pinout |
| | 2.5V – 5.5V operation |
| 8/14-pin DIP Device Adapter | |
| DVA1002 | Supersedes DVA16XP141 |
| | Added support for 2.0V – 5.5V Operation |
| | Added support for Ultra Low Power Wake-up |
| | Added support for OSC2 (FOSC/4) clock out in INTOSC-CLK oscillator mode |
| 8/14/20-pin DIP Device Adapter | |
| DVA1004 | Supersedes DVA1002 |
| | 2.0V – 5.5V Operation |
| | Added support for 20-Pin Devices |
| 64-pin TQFP/80-pin TQFP Device Adapter | |
| DVA18PQ802 | PIC18F6680/8680 pinout |
| | 2.5V – 5.5V operation |
| DVA1003 | Supersedes DVA18PQ802 |
| | Added support for RA7 digital I/O |
| | Added support for 2.0V – 5.5V Operation |