CM1263-02SE

Low Capacitance ESD Protection for High-Speed Serial Interfaces

Features

- 2 Channels of ESD Protection
- 0.85 pF Loading Capacitance per Channel Typical
- Provides ESD Protection to IEC61000-4-2 Level 4:
 - ±8 kV Contact Discharge
 - ±15 kV Air Discharge
- 5-Pin SOT-553 Package
- These Devices are Pb-Free and are RoHS Compliant

Applications

- LCD and Camera Data Lines in Wireless Handsets that Use High-speed Serial Interfaces such as MDDI, MIPI, MVI and MPL
- I/O Port Protection for Mobile Handsets, Notebook Computers, PDAs, etc.
- Wireless Handsets
- Handheld PCs/PDAs
- LCD and Camera Modules




ON Semiconductor®

http://onsemi.com



SOT-553 SE SUFFIX CASE 463B

BLOCK DIAGRAM



MARKING DIAGRAM



L63 = Specific Device Code M = Date Code

ORDERING INFORMATION

Device	Package	Shipping [†]	
CM1263-02SE	SOT-553 (Pb-Free)	5000/Tape & Reel	

†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specification Brochure, BRD8011/D.


1

CM1263-02SE

Table 1. PIN DESCRIPTIONS

5–Pin, SOT–553 Package				
Pin	Description			
1	V _P			
2	V _N			
3	NC			
4	(CH1) ESD Channel #1			
5	(CH2) ESD Channel #2			

PACKAGE / PINOUT DIAGRAM



SPECIFICATIONS

Table 2. ABSOLUTE MAXIMUM RATINGS

Parameter	Rating	Units
Operating Supply Voltage (V _P – V _N)	6.0	V
Operating Temperature Range	-40 to +85	°C
Storage Temperature Range	-65 to +150	°C
DC Voltage at any channel input	$(V_N - 0.5)$ to $(V_P + 0.5)$	V

Stresses exceeding Maximum Ratings may damage the device. Maximum Ratings are stress ratings only. Functional operation above the Recommended Operating Conditions is not implied. Extended exposure to stresses above the Recommended Operating Conditions may affect device reliability.

CM1263-02SE

Table 3. ELECTRICAL OPERATING CHARACTERISTICS (Note 1)

Symbol	Parameter	Conditions	Min	Тур	Max	Units
V _P	Operating Supply Voltage (V _P – V _N)			3.3	5.5	V
l _P	Operating Supply Current	$(V_P - V_N) = 3.3 \text{ V}$			8.0	μΑ
V _F	Diode Forward Voltage Top Diode Bottom Diode	I _F = 8 mA; T _A = 25°C	0.60 0.60	0.80 0.80	0.95 0.95	٧
I _{LEAK}	Channel Leakage Current	$T_A = 25^{\circ}C; V_P = 5 \text{ V}, V_N = 0 \text{ V}, V_{TEST} = 0 \text{ to } 5 \text{ V}$		0.1	1.0	μΑ
C _{IN}	Channel Input Capacitance	At 1 MHz, V _P = 3.3 V, V _N = 0 V, V _{IN} = 1.65 V		0.85	1.2	pF
ΔC_{IN}	Channel Input Capacitance Matching	At 1 MHz, V _P = 3.3 V, V _N = 0 V, V _{IN} = 1.65 V		0.02		pF
V _{ESD}	ESD Protection Peak Discharge Voltage at any channel input, in system: a) Contact Discharge per IEC 61000-4-2 standard b) Air Discharge per IEC 61000-4-2 standard	T _A = 25°C; (Notes 2 and 3) T _A = 25°C; (Note 3)	±8 ±15			kV
V _{CL}	Channel Clamp Voltage Positive Transients Negative Transients	$T_A = 25^{\circ}C$, $I_{PP} = 1$ A, $t_P = 8/20 \ \mu S$ (Note 3)		+9.96 -1.6		V
R _{DYN}	Dynamic Resistance Positive Transients Negative Transients	$\begin{split} I_{PP} = 1 & \text{A, t}_P = 8/20 \ \mu\text{S} \\ \text{Any I/O pin to Ground;} \\ \text{(Note 3)} \end{split}$		0.96 0.5		Ω


^{1.} All parameters specified at $T_A = -40^{\circ}\text{C}$ to $+85^{\circ}\text{C}$ unless otherwise noted.
2. Standard IEC 61000–4–2 with $C_{Discharge} = 150\text{pF}$, $R_{Discharge} = 330~\Omega$, $V_P = 3.3~V$, V_N grounded.
3. These measurements performed with no external capacitor on V_P (V_P floating).





SOT-553-5 1.60x1.20x0.55, 0.50P CASE 463B ISSUE D


DATE 21 FEB 2024



NOTES:

- DIMENSIONING AND TOLERANCING CONFORM TO ASME Y14.5-2018.
- . ALL DIMENSION ARE IN MILLIMETERS.
- 3. MAXIMUM LEAD THICKNESS INCLUDES LEAD FINISH THICKNESS. MINIMUM LEAD THICKNESS IS THE MINIMUM THICKNESS OF BASE MATERIAL.

DIM	MILLIMETERS			
DIIVI	MIN.	NOM.	MAX.	
А	0.50	0.55	0.60	
Ь	0.17	0.22	0.27	
O	0.08	0.13	0.18	
О	1.55	1.60	1.65	
E	1.15	1.20	1.25	
е	0.50 BSC			
Н	1.55	1.60	1.65	
L	0.10	0.20	0.30	



RECOMMENDED MOUNTING FOOTPRINT*

* FOR ADDITIONAL INFORMATION ON OUR Pb-FREE STRATEGY AND SOLDERING DETAILS, PLEASE DOWNLOAD THE ON SEMICONDUCTOR SOLDERING AND MOUNTING TECHNIQUES REFERENCE MANUAL, SOLDERRM/D.

GENERIC MARKING DIAGRAM*



XX = Specific Device Code

M = Date Code

= Pb-Free Package

(Note: Microdot may be in either location)

*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot "•", may or may not be present. Some products may not follow the Generic Marking.

STYLE 1: STYLE 2: STYLE 3: STYLE 4: STYLE 5: PIN 1. CATHODE 2. COMMON ANODE PIN 1. SOURCE 1 PIN 1. BASE 2. EMITTER PIN 1. ANODE 1 2. N/C PIN 1. ANODE 2. EMITTER 2. DRAIN 1/2 3. BASE 4. COLLECTOR 3. CATHODE 2 4. CATHODE 3 3. ANODE 2 4. CATHODE 2 3. BASE 4. COLLECTOR 3. SOURCE 1 4. GATE 1 5. COLLECTOR CATHODE 4 CATHODE 1 5. GATE 2 5. CATHODE

STYLE 6: STYLE 9: STYLE 7 STYLE 8: PIN 1. EMITTER 2 PIN 1. CATHODE 2. COLLECTOR PIN 1. ANODE 2. CATHODE PIN 1. BASE 2. EMITTER 2. BASE 2 **EMITTER 1** 3. BASE 4. COLLECTOR 3. N/C 4. BASE 3. ANODE 4. ANODE 4. COLLECTOR 1 COLLECTOR 2/BASE 1 5. EMITTER 5. ANODE

DOCUMENT NUMBER: 98AON11127D Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.

DESCRIPTION: SOT-553-5 1.60x1.20x0.55, 0.50P PAGE 1 OF 1

onsemi and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.

onsemi, Onsemi, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. Onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi does not convey any license under any of its intellectual property rights nor the rights of others. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA class 3 medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase

ADDITIONAL INFORMATION

TECHNICAL PUBLICATIONS:

 $\textbf{Technical Library:} \ \underline{www.onsemi.com/design/resources/technical-documentation}$

onsemi Website: www.onsemi.com

ONLINE SUPPORT: www.onsemi.com/support

For additional information, please contact your local Sales Representative at

www.onsemi.com/support/sales